How to Fix General Error in Workflow

Kardex Power Pick System




How To Fix General Error In Workflow

This article covers the most common fix for the error message "General error in workflow". However, we cannot cover all the causes in these steps. Please contact Software Support for further support.

If you get the error message below:



Select "Show more details..."




In the section Messages look for "Unable to connect to _____" this is the name of the computer you need to perform the following tasks on.



Restart Service


To restart services, you need to be an Administrator on the computer.

1. Type Services into the Start Menu



Right click and Run as Administrator

2. Scroll Down until you find the PowerPick Machine Control Service



3. If it appears as shown above on the right-hand side, click start





a. If it says Running select Restart

PowerPick Machine Control Service Stop the service Pause the service Restart the service

- b. If you do not have these options please skip to Reboot Computer.
- 4. Retry what you did that got the General error in workflow
- 5. If these steps do not resolve your issue, please place a ticket with Software Support and a Software Analyst will be happy to assist.

Reboot Computer

If you are not an Administrator on the computer, you can try rebooting the computer. This will restart service as part of the process and may resolve your issue. If it does not, please place a ticket with Software Support and a Software Analyst will be happy to assist.

<u>Visit our Customer Knowledge Center for more articles like this.</u>

